


# RAN-GER ALARM

## VOICE INTRUSION SYSTEM

The RAN-GER® RC-9V is an advanced 9 zones wire control panel for residential and light commercial intrusion alarms. Advanced on-board features included automation with event scheduler and combining a wide range of features with easy operation.



### Main Features

- 9 monitoring with programmable zones.
- Pulse delay zone available.
- Support up to 4 LED keypads with a maximum distance of up to 150m.
- 4 private telephones with event report filtering.
- Remote telephones voice guided sessions for status messages, alerts and control options.
- Telephones voice or tones optional interactive menu.
- 2 Central Monitoring System (CMS) numbers and 1 CMS account ID.
- 4 flexible PGM automation features
- Multi-level lightning protection.
- Smoke reset power supply (PGM) on OFF Siren.
- Very easy to operate and configure.

## Product Specifications

Electrical Characteristics	
• DC Input Power supply	AC 16-24V, 50Hz, 3A
• Current consumption	100mA
• Keypad current consumption	100mA
• Backup battery type	12V, 7AH
• Battery cut-off voltage	10.5V
• Battery charging current	600mA
Operation Characteristics	
• Zones	9
• Zones types	Entrance, Internal Delay, Internal, Burglary, 24-hour, Fire and Silent and Force arming.
• Zone connection	NC, NO and EOL
• Keypad Support numbers	Up to 4 LED keypad with a maximum distance of up to 150m.
• 3 quick emergency keys	Fire, Medical, and Panic.
• Arming mode	Home mode and Stay mode Support 1-key fast arming
• PGM Output Numbers	4
• Siren, Aux and PGM output power	12V
• Siren, Aux and PGM output current	2.5A
• Remote telephone guided type	Support Voice or Tone. Support remote arm/disarm, bypass zone, Check status and remote ON/OFF PGM
• CMS Telephone dial out support	Support 2 CMS phone numbers and 1 account ID Support Ademco Contact ID format
• Reporting telephone numbers	4
• Access code	1 Master code, 8 User codes (The 8th User access code used as duress code )

## 5 Channel Protection

### Burglary

*A window is forced open in the middle of the night*

### Threat of Fire

*A fire breaks out while you are sleeping*

### Police Emergency

*An intruder is lurking around your premises*

### Medical Emergency

*When medical help is required*

### Duress

*When you are forced to disarm the system*

